

SF-AC1003EM-WR

Access reader

Access by EM card

LED and acoustic indicator

Wiegand 26/34

Compatible with Safire

Valid for interior



Safire

Access reader for controller

Access by EM card

LED indicator

Wiegand 26/34

Compatible with Safire controllers

Specifications

Brand	Safire
Model	SF-AC1003EM-WR
Activation sensor	Infrared auto-activation
Read time	< 1 Sec.
Card reading distance	< 5 cm
Identification modes	125 KHz EM card
Outputs	RS485, Wiegand 26/34, Buzzer for status indication, Tamper
Compatibility	Safire controllers
Power supply	DC 12 V / 500 mA max.
Degree of protection	IP64
Temp. operation	-20° C ~ +65° C
Dimensions	86.5 (W) x 121 (H) x 14 (D) mm
Weight	140 g